



IJEAST

INTERNATIONAL JOURNAL
OF ENGINEERING APPLIED SCIENCE
AND TECHNOLOGY



VOLUME : 1 ISSUE : 6 Print / Issue Publication Date: 09-Oct-2016



ISSN : 2455-2143



Indexed In



WWW.IJEAST.COM

editor@ijeast.com

A CUSTOMIZED WIDEBAND BANDREJECT FILTER WITH MEANDER LINE AND CROSS COUPLING

Ravi Jaiswal

Department of ECE
MMMUT, Gorakhpur, (U.P), India

B. S. Rai

Department of ECE
MMMUT, Gorakhpur, (U.P), India

G. D. Bharti

Department of ECE
MMMUT, Gorakhpur, (U.P.), India

Abstract— A new customized Wideband Bandreject Filter with Meander line structure and cross coupling. Conventionally the size of Bandreject filter resonator should be in Quarter wave length. With the help of meander line, size of filter can be decreased up to 42%. To convert the long thin microstrip line into meander line, no need of extra calculation is necessary. An extra electric-coupling into two side by side Quarter wave length stubs is achieved, roll-off and sharp skirt successfully attain by introducing two transmissions zero in reject band. A Bandreject filter example is given with calculated attenuation of bandreject filter is 25.5 dB on fractional Bandwidth of 143 % with accessible tool HFSS-13.0, filter is analyzed with available reported result.

Keywords— Bandstop filter (BSF); Meander line; Wideband; Cross coupling.

I. INTRODUCTION

WIDEBAND Band reject filter widely employed in wireless and satellite communication system. Important role of Bandreject filter is to filter out unwanted and surplus signal and allow to pass only preferred signal. In oscillator and Mixer harmonics can be eliminated with the help of Bandreject filter. Sharp skirt and high roll of required in filter when frequency of operation change from passband to stopband. High attenuation in stop band and low insertion loss in passband is requirement of preferred communication system. Typically Microstrip bandreject filter [1] is made off open-circuited Shunt resonators that are $\lambda_g/4$ long with linking lines that also $\lambda_g/4$. This filter with more number of transmissions zero in stop band gives the excellent reject band. As large reject band output is required in band reject filter, the photonic band gap [2] structures and the defected ground plane structures [3] are different solutions. To advance the selectivity and reject band refusal, the introduction of electrical [4] or magnetic [5]–[6] cross couplings and the deployment of several signal transmission paths [9]–[11] have been verified to be two rather professional methods for introducing additional transmission zeros (TZs).

A 4th-order wideband Bandreject filter with stepped-impedance cross-coupled line is presented in this paper. A long thin microstrip cross coupled line is converted in Meander line structure. Meander line structure is useful in dimension attenuation so it is suggested in this proposed work. The projected scheme is very helpful in design of a BSF. By using this procedure we can do diminution in size up to 42%. Band reject filter characteristics can be controlled by Quarter wave length ($\lambda_g/4$) resonator. Dimension of the predicted filter operating frequency is 1.5 GHz and compact size is $0.60 \lambda_g \times 0.05 \lambda_g$. Projected filter has attenuation of 25.5 dB in stop band and fractional bandwidth is 143 %.projected filter getting good accord between mathematical result and simulated result.

II. ANALYSIS OF DESIGN

Band Stop filter [6] made known in Fig.1 as part 1. This band stop filter order is 3, after adding part 2 in part 1 order of filter will change from 3 to 4, Z_{3e}/Z_{3o} will represent the even/odd characteristics Impedance of transmission line The even/odd-mode characteristic Impedance for part 1 is Z_{3e}/Z_{3o} and part 2 is Z_{4e}/Z_{4o} s not similar. For this reason, the arrangement is a sort of coupled line stepped impedance with cross-coupling.




Fig.1 Equivalent circuit of BSF

At the Reject band central frequency f_0 , all transmission line are in proportion measurement lengthwise is $\lambda_g/4$. High order response is realized by introducing the further more introduced capacitances mutually with part 2. For improving the pass band range at upper cut off frequency open circuit shunt stub is converted into stepped impedance resonator, means conversion of UIR into SIR has done. We can carry out

the even and odd mode study because circuit is unique with their geometry. In S-plane, if I/O admittance is equal for even and odd mode then by means of Richard's Transformation-

$$S = j\Omega = j \tan \frac{\pi f}{2f_0} \quad (1)$$

Where Richards, Ω is the normalized element frequency variables, will be given as S , Ω and f are the correspondingly.

(A). Meander Structure design by means of Kotch Curve

The Kotch curve [9] understanding is obtained in notice for predictable new pattern. Up to two iteration of curve is provided in Fig.[2] with the help of Basic Kotch curve style. Basic Kotch curve is used where very thin microstrip line structure is used.




Figure2. Basic Kotch curve arrangement: (a) Zero iteration; (b) 1st iteration; (c) 2nd iteration

The Fig.[a] is given for zero iteration, where the initial length of thin microstrip line (p to q) is d. Fig.[b] is given for first iteration, where the length of microstrip line will get reduced by d/2 and Fig.[c] is given for second iteration, where the length of microstrip line will reduce by d/4. In first iteration the gap between the point p and q is reduced by d/2 and length of unit section line will L/8. In second iteration the distance between p and q is reduced by d/4 and the length of unit

section line will d/64. By using this procedure the length of thin microstrip line can be reduced up to 1/4 times. This procedure can be appropriate for Band stop filter (BSF) and Low pass filter (LPF). In this proposed work, after performing 2nd iteration length of unit section line will very small that will create problem in filter fabrication so we are doing only 1st iteration in this work.

III. EXPERIMENT AND RESULT

A Customized wide bandreject filter with meander line and cross coupling is intended with substrate thickness of 0.73mm, dielectric constant of 2.65 and loss tangent of material will 0.003. The BSF is made up of stepped-impedance coupled line be involve with an open-circuited shunt Stepped impedance resonator (SIR). Proportionate electrical span of $\lambda g/4$, stepped impedance coupled line are used in filter design. Frequency of reject band can be determined with the help of typical impedance ratio and SICL span. Coupling gap between the $\lambda g/4$ resonators is main deciding factor for bandwidth of reject band. Utilize of simulator ANSYS HFSS-13 has done for simulation of anticipated customized Wideband Bandreject Filter with Meander line structure and cross coupling.




Figure 3 estimated design of filter with Meander lines and Stepped Impedance resonator.

Figure 3 illustrate the design of predicted filter. The design of figure (II) is applied to reference [7]. After applying Kotch structure in reference [7] length of Patch reduced by 19%. New structure is again modified by changing the open circuit shunt UIR stub into open circuit shunt SIR stub and two slots have been etched at the surface of substrate. New modified structure is portrayed in figure3. New modified structure length of meander line is 19.45mm. Coupling is increase by reducing gap between the Stepped impedance coupled lines.




Fig.4 Simulated result of the experimental filter.

TABLE I

COMPARISON OF DIFFERENT WIDE BAND BSF

Ref.	Ope. Fre. (GHz)	order	no. of zero	fbw %	attenuation (db)	size ($\lambda_g \times \lambda_g$)
[10]	4	≥ 5	3	47	23	0.181
[7]	2	-	4	100	20	0.109
[8]	1	7	5	140	20	0.056
[5]	1.5	5	5	113.4	34.4	0.040
[this work]	1.5	4	4	143	25.5	0.033

The result of simulated filter is given in Fig.4. Achieved maximum attenuation in reject band is 25.5 dB. Measured insertion loss in lower pass band from (0.01-0.234 GHz) less than 0.28dB and Insertion loss in upper pass band (2.73-3.8 GHz) less than 1.50 dB. The packed size of anticipated filter is $0.601 \lambda_g \times 0.051 \lambda_g$, where λ_g is denotes the guided wavelength of a 50 Ω transmission line on the centre-stopband. Table(I) uncovered the evaluation of the performance of unlike BSF with unlike previous design. The anticipated BSF show immense FBW and a reduced amount of packing in size.

IV. CONCLUSION

The projected method is a doing well and capable of size diminution technique with simplicity. This method of dimension diminution (Meander line structure) can be

imposed on almost every of the long thin transmission line. Projected work diminished the excess of 19% of the dimension with several modifications in the reference diagram of BSF. Converting open circuit shunt Uniform impedance response (UIR) into stepped impedance resonator (SIR) was helpful in the increment of upper pass band filter, some small stubs are used for impedance matching has done to get desired attenuation. Reduction in size has achieved from $0.040 \lambda_g \times \lambda_g$ to $0.033 \lambda_g \times \lambda_g$. A BSF example is given with measured attenuation of stop reject filter is 25.5dB on a fractional bandwidth of 143%

V. REFERENCE

- [1] J. S. Hong and M. J. Lancaster, *Microstrip Filters for RF/Microwave Applications* New York: Wiley, 2001.
- [2] C. Y. Hang, W. R. Deal, T. Qian, and T. Itoh, "High efficiency transmitter front-ends integrated with planar an PBG," in *Asia-Pacific Microwave*
- [3] J.-Y. Kim and H.-Y. Lee, "Wideband and compact bandstop filter structure using double-plane superposition," *IEEE Microw. Wireless Compon. Lett.*, vol. 13, no. 7, pp. 279–280, Jul. 2003.
- [4] S. Y. Huang and Y. H. Lee, "A Tapered Small-Size EBG Microstrip Bandstop Filter Design with Triple EBG Structures," *Microwave and Optical Technology Letters*, Vol. 46, No. 2, 2005, pp. 154-158.
- [5] Si-Wei Ren; Lin-Sheng Wu; Hong-Li Peng; Jun-Fa Mao "Quasi-Elliptic Wideband Bandstop Filter Using Stepped-Impedance Coupled Line" *Microwave and Wireless Components Letters*, , vol.25, Issue 6, pp.364-366, April 2015.
- [6] M.-Y. Hsieh and S.-M. Wang, "Compact and wideband microstrip band stop filter," *IEEE Microw. Wireless Compon. Lett.*, vol. 15, no. 7, pp. 472–474, Jul. 2005
- [7] M. A. Sánchez-Soriano, G. Torregrosa-Penalva, and E. Bronchalo, "Compact wideband bandstop filter with four transmission zeros," *IEEE Microw. Wireless Compon. Lett.*, vol. 20, no. 6, pp. 313–315, Jun. 2010.
- [8] L. Li, Q.-H. Wu, K.Y. Zhao, J. Li, and Y.M. Wang, "Sharp-rejection and ultra-wide Bandstop filter with five transmission zero frequencies," *IET Microw. Antennas Propagation*, vol. 8, no. 2, pp. 80–85, Jan. 2014.
- [9] B. M. Schiffman and G. L. Matthaei, "Exact Design of Band-Stop Microwave Filters," *IEEE Transactions on MTT-12*, 1964, pp. 615.
- [10] H. Shaman and J.-S. Hong, "Wideband bandstop filter with cross-coupling," *IEEE Trans. Microwave. Theory Tech.*, vol. 55, no. 8, pp. 1780–1785, Aug. 2007.

IJEAST

INTERNATIONAL JOURNAL
OF ENGINEERING APPLIED SCIENCE
AND TECHNOLOGY

ABOUT IJEAST

International Journal of Engineering Applied Science and Technology (IJEAST) is a peer-reviewed, open access journal that publishes high-quality research papers in the field of Engineering, Applied Science and Technology.

IJEAST aims to provide a platform for researchers, academicians, and professionals to share their innovative ideas, research findings, and practical experiences with the global scientific community.

FOCUS AREAS

- Engineering
- Applied Science
- Technology
- Innovation & Development
- Interdisciplinary Studies



PEER REVIEWED

All submissions are rigorously peer reviewed to ensure quality.



OPEN ACCESS

Free and unrestricted access to research for all.



GLOBAL REACH

Connecting researchers and professionals worldwide.



TIMELY PUBLICATION

We ensure a swift and efficient publication process.



For more information, visit our website

www.ijeast.com



INTERNATIONAL JOURNAL

OF ENGINEERING APPLIED SCIENCE
AND TECHNOLOGY



editor@ijeast.com



www.ijeast.com



India



2455-2143